AiT Semiconductor Inc.

DESCRIPTION

A6110B series are a group of positive voltage output, high precise, and low power consumption voltage regulator. Voltages are selectable in 100mV steps within a range of 1.2V to 5.0V. It also can be customized on command.

A6110B series have excellent load and line transient response and good temperature characteristics, which can assure the stability of chip and power system. And it uses trimming technique to guarantee output voltage accuracy within ±2%.

The A6110B is available in SOT-25 package.

ORERING INFORMATION

Package Type	Part Number			
SOT-25	FE	A6110BE5R-XX		
SPQ: 3,000pcs/Reel	ED	A6110BE5VR-XX		
	XX: Output Voltage			
Note	V: Halogen free Package			
	R: Tape & Reel			
AiT provides all RoHS products				

FEATURES

- Low Quiescent Current: 100µA at 5V
- High PSRR: 65dB range to 1kHz
- Low Output Noise: 44uVRMS
- Low Dropout: 200mV@Iout=0.8A, Vout=3.3V
- Maximum output current: 1A
- Highly Accurate: ±2%
- Low ESR Ceramic Capacitor Compatible
- Available in SOT-25 package.

APPLICATION

- Reference Voltage Source
- Battery Powered Equipment
- PC Peripherals
- Wireless Devices
- Instrumentation

TYPICAL APPLICATION





PIN DESCRIPTION





ABSOLUTE MAXIMUM RATINGS

Max Input Voltage		8V
T _J , Max Operating Junction Temperature		145°C
T _A , Ambient Temperature		-40°C ~85°C
Power Dissipation	SOT-25	250mW
Ts, Storage Temperature		-40°C~150°C
Lead Temperature & Time		260°C, 10sec

Stresses above may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated in the Electrical Characteristics are not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

RECOMMENDED WORK CONDITIONS

Parameter	Symbol	Value	Units	
Input Voltage Range		Max. 6	V	
Ambient Temperature		-40 ~85	°C	
Operating Junction Temperature	TJ	125	°C	



ELECTRICAL CHARACTERISTICS

Peromotor	Symbol	Conditions		Min	Typ	Mox	Linito
Farameter	Symbol	Conditions			тур	IVIAX	Units
Input Voltage V _{DD}				1.5	-	6	V
				NOTE1			
Output Voltage	Vout	V _{DD} =Set V _{OUT} +1V 1mA≤l _{OUT} ≤10mA	Vout>1.5	Vout	Vouт	Vout	V
				X0.98		X1.02	
			V15	Vout		Vout	
			VOUT~-1.5	-0.03		+0.03	
Maximum Output	IOUT (Max.)		•				
Current	NOTE2	Vdd-Vout=1V		1	-	-	A
Dropout Voltage	VDROP	Vout =3.3V, Iout=1A		-	300	500	mV
Line Regulation	ΔV _{OUT}			-	0.05	0.2	%/V
	$\Delta V_{\text{IN}} \times V_{\text{OUT}}$	$100T = 10 \text{ mA}, 4V \leq V_{\text{f}}$					
Load Regulation	Vout	V _{DD} =Set V _{OUT} +1V 1mA≤I _{OUT} ≤2.5A		-	30	60	mV
Output Voltage		I _{OUT} =10mA		-	±100	-	ppm/°C
Temperature	ΔVουτ						
Coefficient	$\Delta T \times V_{\text{OUT}}$						
Ripple Rejection	PSRR	f=100Hz, Ripple=0.5Vp-p, V _{DD} =Set V _{OUT} +1V		-	65	-	dB
EN Input Voltage "L"	VENL			0	-	0.25	V
Output Noise	en	BW=10Hz~100kHz		-	44	-	uVrms

.... ----.

NOTE1: I_{OUT}=350mA@V_{IN}=1.5V, V_{OUT}=1.2V

NOTE2: The maximum power rating of each package is a constant, so along with the change of ILOAD, the VDD-VOUT should be controlled to a certain range to ensure the normal operation.



TYPICAL PERFORMANCE CHARACTERISTIC



3. Line Regulation



5. Dropout Voltage





4. lq



6. V_{OUT} vs. Temperature





Load Transient Response (VIN=5V, VOUT=3.3V) CIN=1uF, COUT=1uF, IOUT=1mA-100mA



8. Line Transient Response(V_{IN}=5V,V_{OUT}=3.3V) C_{IN}=1uF,C_{OUT}=1uF,I_{OUT}=10mA,V_{IN}=4.3V-5.3V



BLOCK DIAGRAM





PACKAGE INFORMATION

Dimension in SOT-25 (Unit: mm)









IMPORTANT NOTICE

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc.'s integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or servere property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.