BRIDGE RECTIFIER

1A FORWARD CURRENT, 100 TO 1000V REVERSEVOLTAGE

## **DESCRIPTION**

The MB1FR ~ MB10FR are available in MBF Package

- High Surge Current Capability
- Designed for Surface Mount Application
- Reverse Voltage 100 to 1000 V
- Forward Current 1A

# **MECHANICAL DATA**

Case: MBF

Terminals: Solderable per MIL-STD-750,


Method 2026

Approx. Weight: 75mg / 0.0024oz

## PIN DESCRIPTION

# ORDERING INFORMATION

Package Type	Part Number			
MBF	MB1FR			
	MB2FR			
	MB3FR			
	MB4FR			
	MB5FR			
	MB6FR			
	MB7FR			
	MB8FR			
	MB9FR			
	MB10FR			
SPQ	5,000 pcs/Reel			
AiT provides all RoHS Compliant Products				



MBF Package

PIN#	DESCRIPTION			
1	Input Pin ( ~ )			
2	Input Pin ( ~ )			
3	Output Anode ( + )			
4	Output Cathode ( - )			

REV1.0 - APR 2023 RELEASED - -1

1A FORWARD CURRENT, 100 TO 1000V REVERSEVOLTAGE

# **MAXIMUM RATINGS & ELECTRICAL CHARACTERISTICS**

Ratings at 25°C ambient temperature unless otherwise specified.

Single phase half-wave 60 Hz, resistive or inductive load, for capacitive load current derate by 20 %.

Parameter	Symbol	MB1FR	MB2FR	MB4FR	MB6FR	MB8FR	MB10FR	Unit
Maximum Repetitive Peak	.,	400	222	400	000	222	4000	
Reverse Voltage	V <sub>RRM</sub>	100	200	400	600	800	1000	V
Maximum RMS Voltage	V <sub>RMS</sub>	70	140	280	420	560	700	V
Maximum DC Blocking		400					4000	
Voltage	V <sub>DC</sub>	100	200	400	600	800	1000	V
Average Rectified Output		1						А
Current at T <sub>A</sub> = 40 °C	lo							
Peak Forward Surge Current		25						А
8.3 ms Single Half Sine								
Wave Superimposed on	I <sub>FSM</sub>	35						
Rated Load (JEDEC Method)								
Maximum Forward Voltage	.,						V	
at 1 A	V <sub>F</sub> 1.1					V		
Maximum DC Reverse							μА	
Current at Rated DC		5						
Blocking Voltage T <sub>A</sub> = 25 °C								
Maximum DC Reverse								
Current at Rated DC	I <sub>R</sub>	100						
Blocking Voltage T <sub>A</sub> =100 °C								
Maximum DC Reverse								
Current at Rated DC		500						
Blocking Voltage T <sub>A</sub> =125 °C								
Typical Junction Capacitance (1)	Cj	13				pF		
T : 1T	R <sub>θ</sub> JA	60					°C/W	
Typical Thermal Resistance (2)	Rejl	16						
Operating and Storage	TJ	-55 ~ +150			°C			
Temperature Range	Tstg	-55 ~ +150			°C			

<sup>(1)</sup> Measured at 1 MHz and applied reverse voltage of 4 V D.C

REV1.0 - APR 2023 RELEASED - - 2 -

<sup>(2)</sup> Mounted on glass epoxy PC board with 1.3mm2 copper pad.



1A FORWARD CURRENT, 100 TO 1000V REVERSEVOLTAGE

#### TYPICAL PERFORMANCE CHARACTERISTICS

Fig 1. Average Rectified Output Current **Derating Curve** 




Fig 2. Typical Reverse Characteristics




Fig3. Typical Instantaneous Forward Characteristics




Fig4. Typical Junction Capacitance





Fig5. Maximum Non-Repetitive Peak Forward Surge Current





**REV1.0** - APR 2023 RELEASED -- 3 -


BRIDGE RECTIFIER
1A FORWARD CURRENT, 100 TO 1000V REVERSEVOLTAGE


# PACKAGE INFORMATION

Dimension in MBF (Unit: mm)









THE RECOMMENDED MOUNTING PAD SIZE

Symbol	Min	Max		
Α	1.20	1.60		
а	-	0.20		
С	0.15	0.22		
D	4.50	5.00		
d	2.30	2.70		
Е	3.60	4.10		
е	0.50 0.70			
HE	6.40 7.00			
L	1.30	1.70		
L1	0.50 1.10			
θ	7°			

REV1.0 - APR 2023 RELEASED -

MB1FR\_MB10FR

BRIDGE RECTIFIER
1A FORWARD CURRENT, 100 TO 1000V REVERSEVOLTAGE

## **IMPORTANT NOTICE**

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc.'s integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or serve property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.

REV1.0 - APR 2023 RELEASED - - 5 -