# DESCRIPTION

The ES2AF\_ES2JF are available in SMAF package.

#### **FEATURE**

- For Surface Mounted Applications
- Low Profile Package
- Glass Passivated Chip Junction
- Superfast Reverse Recovery Time

## **MECHANICAL DATA**


Case: SMAF

Terminals: Solderable per MIL-STD-750,

Method 2026

Approx. Weight: 27mg / 0.00086oz

# PIN DESCRIPTION



### ORDERING INFORMATION

Package Type	Part Number			
	ES2AF			
SMAF	ES2BF			
	ES2CF			
	ES2DF			
	ES2EF			
	ES2GF			
	ES2JF			
Note	SPQ: 3,000pcs/Reel			
AiT provides all RoHS Compliant Products				

PIN#	DESCRIPTION			
1	CATHODE			
2	ANODE			

RECTIFIER DIODE REVERSE VOLTAGE 50V TO 600V FORWARD CURRENT 2A

### ABSOLUTE MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase half-wave 60Hz, resistive or inductive load, for capacitive load current derate by 20 %.

Parameter		hbol ES2AF ES2BF ES2CF ES2DF ES2EF ES2GE ES2JF						I Inite		
		Cyllibol	LOZAF	LOZDF	LOZUF	LOZDF	LOZLI	LOZGE	LOZUF	Office
Maximum Repetitive Peak Reverse		$V_{RRM}$	50	100	150	200	300	400	600	V
Voltage		TATAW								
Maximum RMS Voltage		V <sub>RMS</sub>	35	70	105	140	210	280	420	٧
Maximum DC Blocking Voltage		$V_{DC}$	50	100	150	200	300	400	600	V
Maximum Average Forward Rectified			2						А	
Current at T∟ = 100 °C		I <sub>F(AV)</sub>								
Peak Forward Surge Current 8.3ms										
Single Half Sine Wave Superimposed		I <sub>FSM</sub>	50							Α
on Rated Load (JEDEC Method)										
Maximum Forward Voltage at 2A		V <sub>F</sub>	1	1	1	1	1.25	1.25	1.7	V
Maximum DC Reverse	T <sub>A</sub> = 25°C		5							
Current at Rated DC		l <sub>R</sub>								
Blocking Voltage	T <sub>A</sub> =125°C		100							μΑ
Typical Junction Capacitance			00							pF
at V <sub>R</sub> =4V, f=1MHz		C <sub>j</sub>		60						
Maximum Reverse Recovery Time at I <sub>F</sub> =0.5A, I <sub>R</sub> =1A, I <sub>rr</sub> =0.25A		t <sub>rr</sub>	35						ns	
										Operating Temperature Range
Storage Temperature Range		T <sub>stg</sub>	-55 ~ <b>+</b> 150						°C	


Stresses above may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated in the Electrical Characteristics are not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

www.ait-ic.com

RECTIFIER DIODE **REVERSE VOLTAGE 50V TO 600V FORWARD CURRENT 2A** 

#### TYPICAL PERFORMANCE CHARACTERISTICS

Fig1. Reverse Recovery Time Characteristic and Test Circuit Diagram






Fig2. Maximum Average Forward Current Rating




Fig3. Typical Reverse Characteristics




Fig4. Typical Forward Characteristics





Fig5. Typical Junction Capacitance




www.ait-ic.com

**AiT Semiconductor Inc.** 


RECTIFIER DIODE REVERSE VOLTAGE 50V TO 600V FORWARD CURRENT 2A

# PACKAGE INFORMATION

Dimension in SMAF Package (Unit: mm)



#### The recommended mounting pad size



SYMBOL	MIN	MAX			
Α	0.900	1.100			
С	0.120	0.200			
D	3.300	3.700			
E	2.400	2.700			
е	1.300	1.600			
g	0.800	1.200			
H <sub>E</sub>	4.400	4.900			
2	7°				

ES2AF\_ES2JF

RECTIFIER DIODE REVERSE VOLTAGE 50V TO 600V FORWARD CURRENT 2A

### **IMPORTANT NOTICE**

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc. integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or server property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.